384 Universal voltage/cable type BGS-2V series

Standard BGS model A renewal of the BGS-V series

- **Dual lens achieves long range detection**
- Maximum sensing distance of 1 m
- Universal voltage type that eliminates the need to choose power supply









Long range detection of black workpieces



Detection of printed cardboard passage



Detection of knotty or grainy lumber



Detection of magazines passing on a rolling conveyor



Selection table

| Time | Chana | Tuna | Sensing distance | Model | |
|--------------|-------|----------------------|--|-----------------------------|-----------------------------|
| Туре | Shape | Туре | (Adjustable distance range shown in parentheses) | NPN type | PNP type |
| BGS model | | DC power | 10 to 300 mm (100 to 300 mm) | BGS-2V30N (BGS-2V30CN) | BGS-2V30P (BGS-2V30CP) |
| | | | 20 to 500 mm (150 to 500 mm) | BGS-2V50N (BGS-2V50CN) | BGS-2V50P (BGS-2V50CP) |
| | | | 20 to 1000 mm (250 to 1000 mm) | BGS-2V100N (BGS-2V100CN) | BGS-2V100P (BGS-2V100CP) |
| Туре | Shape | Туре | Sensing distance (Adjustable distance range shown in parentheses) | Мо | del |
| BGS model | | Universal voltage | 10 to 300 mm (100 to 300 mm) | BGS-2V30 | |
| | | | 20 to 500 mm (150 to 500 mm) | BGS-2V50 | |
| | | | 20 to 1000 mm (250 to 1000 mm) | BGS-2 | 2V100 |

[•] For the connector type, please purchase an optional DOL-1204-G02M connector cable.

Options/Accessories

Connector cables For BGS-2V30CN/-2V50CN/-2V100CN

Straight



DOL-1204-G02M Cable length: 2 m

Protective mounting bracket

For BGS-2V series

- Ultra-durable 3 mm thick type Rust-resistant stainless steel
- Sensor is firmly secured using M4 Hex socket head cap screws
 The bracket is also firmly secured using an M6 screws

LV2 series





LV2-S01

Photoelectric Sensors

Photoelectric Sensors

Laser Displacement Sensors

Long-range BGS Sensors

TOF-L

TOF-DL TOF-3V

Output status and stability can be checked at a glance

Easy-to-see dual indicators Renewal

In place of the (red) light receiving indicators of the conventional model, the new type has both output indicators (orange) and stability indicators (green). Now it's possible to confirm not only the sensor output but also the detection stability.



Can be used with any voltage

Relay for universal voltage type Renewal

Universal voltage/cable type BGS-2V series

Equipped with an IP67 relay that has obtained VDE standard certification The sensor also conforms to IP67 and the relay inner structure features double dust- and water-resistance. In addition, contact point capacity has been increased to 3 A (at 250 VAC).



Dual lens achieves long range detection

Long range type (BGS-2V100□)

Because a dual lens is used, LED light is condensed by two lenses.

For that reason, stable light is emitted, making long-range detection possible.

Aperture 3° ø33 mm ø27 mm Emitting LED Dual lens 1000 mm 600 mm Sensing distance

For improved maintenance

Pivot type M12 connector

A connector type convenient for replacing sensors or only cables during maintenance is also available. Ideal for use in cleanrooms where the usage of items such as tools is undesirable.



Easy adjusting

Finely adjustable 2-turn potentiometer

Features a wide distance adjustment range to enable fine distance determinations to be made.

Since these models also come with indicators, the adjustment position can be confirmed at a glance.



Water resistant structure

Degree of protection on IP67

Achieves a IP67 level of water resistance. Can be used without worry in factories or with devices in which contact with water occurs.

Note: Water or oil that adhere to the optical surface could cause light to refract and prevent detection from being performed correctly.



Specifications

Universal voltage/cable type BGS-2V series

DC power type

| Туре | | / ре | Short-range | Mid-range | Long-range | | |
|-------------------------------------|----------------------|---------------------|---|-----------------------------|------------------------------|--|--|
| | NPN | Cable type | BGS-2V30N | BGS-2V50N | BGS-2V100N | | |
| Mod | | Connector type | BGS-2V30CN | BGS-2V50CN | BGS-2V100CN | | |
| | PNP | Cable type | BGS-2V30P | BGS-2V50P | BGS-2V100P | | |
| | PNP | Connector type | BGS-2V30CP | BGS-2V50CP | BGS-2V100CP | | |
| Sensing distance | | ance | 10 to 300 mm ⁻¹ | 20 to 500 mm ⁻¹ | 20 to 1000 mm ⁻¹ | | |
| Adjustable distance range | | istance range | 100 to 300 mm ^{*1} | 150 to 500 mm ^{*1} | 250 to 1000 mm ⁻¹ | | |
| Light source | | | Red LED | | | | |
| Response time | | ne | 2 ms (| 3 ms or less | | | |
| Hysteresis | | | 5% or less 15% or less | | | | |
| Distance adjustment | | ustment | 2-turn potentiometer | | | | |
| Indicators | | | Output indicator: Orange LED, Stability indicator: Green LED | | | | |
| Control output | | ut | NPN/PNP type open collector Max. 100 mA/30 VDC | | | | |
| Output mode | | | Light ON / Dark ON switched by wiring | | | | |
| Connection type | | type | Cable type: Cable length: 2 m, ø3.8 mm Connector type: M12, 4-pin | | | | |
| Insulation resistance | | sistance | 20 MΩ or more (with 500 VDC) | | | | |
| Supply voltage Current consumption | | voltage | 10 to 30 VDC | | | | |
| Rat | Current consumption | | 35 mA or less | | | | |
| Applicable regulations | | egulations | EMC directive (2004/108/EC) | | | | |
| Applicable standards | | tandards | EN 60947-5-2 | | | | |
| Company standards | | andards | Noise resistance: Feilen Level 3 cleared | | | | |
| a | Ambient to | emperature/humidity | -25 to +55°C (no freezing) / 35 to 85% RH | | no condensation) | | |
| nent Jce | Ambient illuminance | | Sunlight: 10,000 lx Incandescent lamp: 3,000 lx | | | | |
| Environmental resistance | Vibration resistance | | 10 to 55 Hz; double amplitude 1.5 mm; 2 hours in each of the X, Y, and Z directions | | | | |
| resi | Shock resistance | | Approx. 50 G (500 m/s²), 3 times in each of the X, Y, and Z directions | | | | |
| р_ | Degree of protection | | IEC standard, IP67 | | | | |
| Mate | Material | | Housing: ABS (glass fiber filled, fire resistant), Front cover: Polycarbonate | | | | |
| Weig | Weight without cable | | Approx. 50 g | | | | |
| | | | | | | | |

Mounting bracket: BEF-W250

Included accessories

Photoelectric Sensors

Specialized Photoelectric Sensors

Laser Displacement Sensors

TOF-L

TOF-DL

TOF-3V

^{*1.} Using a 200 mm × 200 mm white sheet of paper.

[•] Specifications are subject to change without prior notice for product improvement purposes.

■ Universal voltage type

| Type | | | Short-range | Mid-range | Long-range | | |
|---------------------------|------------------|-----------------|--|------------------------------|------------------------------|--|--|
| Mod | Cable | e type | BGS-2V30 | BGS-2V50 | BGS-2V100 | | |
| | Conn | ector type | _ | _ | _ | | |
| Sens | Sensing distance | | 10 to 300 mm ⁻¹ | 20 to 500 mm ⁻¹ | 20 to 1000 mm ^{*1} | | |
| Adjustable distance range | | nce range | 100 to 300 mm ⁻¹ | 150 to 500 mm ⁻¹ | 250 to 1000 mm ⁻¹ | | |
| Light source | | | Red LED | | | | |
| Response time | | | 15 ms or less | | | | |
| Hysteresis | | | 5% or less | | 20% or less | | |
| Distance adjustment | | ment | 2-turn potentiometer | | | | |
| Indicators | | | Output indicator: Orange LED, Stability indicator: Green LED | | | | |
| Control output | | | Relay × 1C ⁻² 250 VAC/3 A or less, 30 VDC/2 A or less (load resistance) | | | | |
| Output mode | | | Fixed to Light ON | | | | |
| Connection type | |) | Cable type: Cable length: 2 m, ø6.4 mm | | | | |
| Insulation resistance | | ance | 20 MΩ or more (with 500 VDC) | | | | |
| Rating | Supply volta | age | 24 to 240 VAC, 24 to 240 VDC | | | | |
| Rat | Current cor | nsumption | 2.5 VA or less | | | | |
| Applicable regulations | | ations | EMC directive (2004/108/EC), Low voltage directive (2006/95/EC) | | | | |
| Applicable standards | | dards | EN 60947-5-2 | | | | |
| Company standards | | ards | Noise resistance: Feilen Level 3 cleared | | | | |
| | Ambient temper | rature/humidity | -25 to +55°C (no freezing) / 35 to 85% RH (no condensation) | | | | |
| Environmental resistance | Ambient illu | ıminance | Sunlight: 10,000 lx Incandescent lamp: 3,000 lx | | | | |
| vironment esistance | Voltage resi | istance | 2700 VAC / minute | | | | |
| riror Ssist | Vibration re | sistance | 10 to 55 Hz; double ampli | f the X, Y, and Z directions | | | |
| Env | Shock resis | stance | Approx. 50 G (500 m/s²), 3 times in each of the X, Y | | Y, and Z directions | | |
| | Degree of p | rotection | IEC standard, IP67 | | | | |
| Material | | | Housing: ABS (glass fiber filled, fire resistant), Front cover: Polycarbonate | | | | |
| Weight without cable | | able | Approx. 50 g | | | | |
| Included accessories | | ories | Mounting bracket: BEF-W250 | | | | |

^{*1.} Using a 200 mm × 200 mm white sheet of paper.

Photoelectric Sensors

Specialized Photoelectric Sensors

Laser Displacement Sensors

Long-range BGS Sensors

TOF-L

TOF-DL

TOF-3V

BGS-2\

^{*2.} When driving the inductive load (with an induction valve, electromagnetic contactor, etc.) through the relay connection point, please use a noise absorption device (surge absorber).

[•] Specifications are subject to change without prior notice for product improvement purposes.


[•] Products certified for the Chinese CCC compulsory certification system also available. Please inquire for details.

specialized Photoelectric Sensors

Universal voltage/cable type BGS-2V series

I/O circuit diagram

■ NPN output type (DC power type)



Photoelectric Sensors

Specialized Photoelectric Sensors

Laser Displacement Sensors


Long-range BGS Sensors

TOF-L TOF-DL


TOF-3V

BGS-2V

■ Universal voltage type



■ PNP output type (DC power type)



■ DC power connector type

Sensor side Connector cable side



- ① 10 to 30 VDC ② Not connected
 - ② Not connected/ +V: Light ON (NPN) 0 V: Dark ON
 - ③ 0 V
 - ④ Control output

Connecting

- Turns to Light ON mode when the white wire is connected to +V or not connected and to Dark ON mode when connected to 0 V (for NPN). To use without connecting, disconnect and wrap individually with insulating tape, etc. Do not connect it to any other terminal.
- 1 to 4 are connector pin No.

Notes

- When using a switching regulator for the power supply, be sure to ground the frame ground terminal.
- Wiring sensor cables with high-voltage or power supply lines can result in malfunctions due to noise, which can cause damage, make sure to wire separately.
- Avoid using the transient state while the power is on (approx. 150 ms).

(Unit: mm)

Specialized Photoelectric Sensors

Laser Displacement Sensors

Long-range BGS Sensors

> TOF-L TOF-DL


TOF-3V


BGS-2\

Dimensions


Sensor


■ Cable type





Connector type






24.7

| | BGS-2V30□ | BGS-2V50□ | BGS-2V100□ |
|---|-----------|-----------|------------|
| а | 12.6 | 13 | 13.6 |
| | | | |

Connector cables

■ DOL-1204-G02M



Cable section material: PVC Conductor cross-section: $4\text{-wire} \times 0.25 \text{ mm}^2$


Universal voltage/cable type BGS-2V series

Dimensions

Mounting bracket

■ Cable type

■ Connector type




Photoelectric Sensors


Specialized Photoelectric Sensors

Laser Displacement Sensors


TOF-L TOF-DL


TOF-3V







Mounting bracket (included) ■ BEF-W250












(Unit: mm)


Specialized Photoelectric Sensors


Typical characteristic data


*Please contact a sales representative for any other characteristic data that may be required.

BGS-2V30□









Photoelectric Sensors

Specialized Photoelectric Sensors

Laser Displacement Sensors


Long-range BGS Sensors


TOF-LL


TOF-3V


BGS-2V

BGS-2V50□









BGS-2V100□

